


INSTRUCTION SHEET

CPDB 160, CPDB 250, CPDB 400
 (2112101926, 2112101928, 2112101922, 2112101929)



SEP One pole DIN-rail distribution block, 160A / 11,8kA


CPDB 160A
 2112100160



SEP One pole DIN-rail distribution block, 250/400A / 24,5kA

CPDB 250
 2112100250

CPDB 400
 2112100400



					CPDB160 2112100160	CPDB250 2112100250	CPD400 2112100400
	4 Nm	10mm ² - 70mm ²	10mm ² - 70mm ²	HEX 5	1x		
	19 Nm	35mm ² - 120mm ²	35mm ² - 95mm ²	HEX 6		1x	
	25 Nm	35mm ² - 185mm ²	35mm ² - 150mm ²	HEX 8			1x
	2 Nm	2,5mm ² - 10mm ²	1,5mm ² - 10mm ²	M4		4x	4x
	2 Nm	2,5mm ² - 16mm ²	1,5mm ² - 16mm ²	M4	6x	5x	5x
	3,5 Nm	6mm ² - 35mm ²	2,5mm ² - 25mm ²	M4		2x	2x

Note:

Unused openings should be tighten to a torque of 0,5 - 1 Nm

WARNING:

All products shall be installed and used as indicated by SEP Europe in the instruction sheets and training materials. Products must never be used for a purpose other than which they were designed for or in a manner that exceeds the specified ratings. Installations must be carried out in accordance with the applicable national rules for electrical installations.